

Briggs & Stratton 100 Amp, 16 Circuit Automatic Transfer Switch Model Number ATS-071047



*The 100 amp, 16 circuit automatic transfer switch provides power to select number of circuits.
Flexible, indoor/outdoor placement makes it convenient and easy to install.
Nema 3R rated for maximum protection against dirt, rain, sleet and snow.
Recommended for use with 8-20kW Briggs & Stratton home stand-by generators.*

Specifications

Length (in.)	6
Width (in.)	14
Height (in)	24
Weight (lbs)	39
Amperage	100A
Voltage	120/240V
Phase	Single (2 pole)
Lug Range	#14 - #6
Breakers Included (Cutler-Hammer BR style)	
8 x 20A 1P, 1 x 30A 2P, 1 x 40A 2P, 2 x 50A 2P	
cUL Approved	

NOT RATED FOR SERVICE ENTRANCE USE



Ph: 800-690-2396

sales@sommersgen.com